

1	ACDC_TOPSwitchJX_062521; Rev.2.1; Copyright Power Integrations 2021	INPUT	INFO	OUTPUT	UNITS	TOPSwitch-JX Flyback Design Spreadsheet
2	<b>Application Variables</b>					<b>Design Title</b>
3	VAC_RANGE			Universal		Input voltage range
4	VAC_MIN			85 V		Minimum input RMS voltage
5	VAC_MAX			265 V		Maximum input RMS voltage
6	FL			50 Hz		Line frequency
7	VOUT	24.00		24.00 V		Output voltage
8	IOUT			5.00 A		Output current
9	POUT	120.0		120.0 W		Output power
10	POUT_PEAK			120.0 W		Peak output power
11	EFFICIENCY_ACDC			0.86		AC-DC efficiency
12	FACTOR_Z			0.50		Z-factor
13						
14						
15	<b>Input Side Components</b>					
16	<b>Input Capacitor</b>					
17	CIN	330.0		330.0 uF		Input capacitance
18	VF_BRIDGEDIODE			0.70 V		Input bridge diode forward voltage
19	VAC_MIN_VLY			89.4 V		Valley of the rectified minimum input AC voltage when delivering POUT. During peak power delivery, the valley of the rectified minimum input AC voltage is 89.4V
20						
21	<b>V-Pin</b>					
22	UVOV TYPE	UVOV		UVOV		Standard under-voltage and over-voltage. Refer to page.13 of the TopSwitch-JX spreadsheet
23	UNDERVOLTAGE			62.5 - 78.6 V		Actual RMS under-voltage range
24	OVERVOLTAGE			301.7 - 337 V		Actual RMS over-voltage range
25	RLS1			4.02 MΩ		1% resistor connected from the rectified line voltage to the V-pin
26	RLS2			NA kΩ		Not required
27						
28	<b>X-Pin</b>					
29	KI			0.725 - 0.934		Typical current limit reduction factor target
30	ILIMIT_KI_RANGE			3.485 - 5.17 A		Minimum current limit based on KI
31	RIL			8.87 kΩ		Current limit programming resistor (1%) connected to the X-pin. Refer to page.31 of the TOPSwitch-JX datasheet
32	RPL			19.600 MΩ		Power limiting resistor (1%) connected from the rectified input voltage to the X-pin. Refer to page.14 of the TOPSwitch-JX datasheet
33						
34	<b>Bias Winding</b>					
35	VBIAS			12.00 V		Target rectified bias winding voltage at low-load
36	VF_BIAS			0.70 V		Bias winding rectifier diode on-time voltage drop
37	VBIAS_OVP			18.00 V		Target rectified bias winding voltage to trigger output over-voltage
38	VZ_OVP			16.00 V		Zener voltage (1%) required for bias winding sensed output over-voltage. Refer to fig.15 in the TOPSwitch-JX datasheet
39	R_OVP			3.74 kΩ		Resistor (1%) required for bias winding sensed output over-voltage. Refer to fig.15 in the TOPSwitch-JX datasheet
40						
41						
42	<b>TOPSwitch-JX</b>					
43	PACKAGE	eSIP-7C		eSIP-7C		TOPSwitch Package
44	HEATSINK	Metal		Metal		TOPSwitch Heatsink
45	ENCLOSURE	Open Frame		Open Frame		Power supply enclosure
46	MODE_FREQUENCY	F		F		Frequency operation mode (F=132kHz, H=66kHz)
47	DEVICE	TOP271		TOP271EG		TOPSwitch device
48	PMAX			177 W		TOPSwitch device maximum power capability
49	ILIMIT_MIN			4.808 A		Minimum TOPSwitch current limit
50	ILIMIT_MAX			5.532 A		Maximum TOPSwitch current limit
51	VDSON			2.695 V		TOPSwitch on-time drain to source voltage
52	VDSOFF			563.4 V		TOPSwitch off-time drain to source voltage
53						
54						
55	<b>Electrical Parameters (Worst Case)</b>					
56	KP	0.500		0.463		Measure of continuous/discontinuous mode of operation. The actual KP calculated based on tolerance may be lower than the value entered
57	DUTY			0.618		Primary switch duty cycle
58	Iavg_PRI			1.497 A		Primary switch average current
59	IPK_PRI			3.409 A		Primary switch peak current
60	IRMS_PRI			1.957 A		Primary Switch RMS current
61	IRIPPLE_PRI			3.090 A		Primary Switch ripple current
62	IPK_SEC			19.600 A		Secondary rectifier peak current
63	IRMS_SEC			8.853 A		Secondary winding RMS current
64						
65						
66	<b>Transformer</b>					
67	LP_TYP			240.5 uH		Typical primary magnetizing inductance
68	LP_RANGE			228.5 - 252.5 uH		Range of primary magnetizing inductance to ensure power delivery
69	LP_TOL			5.0 %		Magnetizing inductance tolerance

70	VOR	140.0		140.0	V	Secondary winding voltage reflected to the primary winding
71						
72	<b>Core/Bobbin Selection</b>					
73	CORE	PQ32/20		PQ32/20		Transformer core selection - refer to the Transformer Parameters tab to verify fit
74	CORE CODE			B65879A0000R095		Core code
75	AE			154.2	mm^2	Core cross sectional area
76	LE			48.4	mm	Core magnetic path length
77	AL			7600	nH/turns^2	Ungapped core effective inductance
78	VE			7460	mm^3	Core volume
79	BOBBIN			B65880E0012D001		Bobbin
80	AW			47.00	mm^2	Window area of the bobbin
81	BW			9.10	mm	Bobbin width
82	MARGIN			0.00	mm	Safety margin width (Half the primary to secondary creepage distance)
83						
84	<b>Winding Parameters</b>					
85	NP			23		Primary winding number of turns
86	NB			3		Bias winding number of turns
87	NS			4		Secondary winding number of turns
88	BPEAK			0.3680	T	Transformer core's peak flux density
89	BMAX			0.2360	T	Transformer core's operating flux density
90	BAC			0.0634	T	Transformer core AC flux density (0.5 x Peak-Peak)
91	ALG			454.6	nH/turns^2	Gapped core effective inductance (Typical)
92	LG			0.40	mm	Core gap length
93						
94						
95	<b>Output Stage</b>					
96	<b>Output 1</b>					
97	VOUT1			24.00		Output voltage
98	IOUT1			5.00		Output current
99	POUT1			120.00		Output power
100	IRMS_SEC1			8.853		Secondary winding RMS current
101	IRIPPLE_COUT1			7.306		Output capacitor ripple current
102	NS1			4		Secondary winding number of turns
103	VDSOFF_DIODE1			88.9		Output rectifier off-time voltage stress (not incl. the parasitic ring)
104	PN_DIODE1			SBR10150		Suggested output rectifier schottky diode
105	VRRM_DIODE1			150		Output rectifier rated reverse repetitive voltage
106	VF_DIODE1			0.92		Output rectifier rated on-time voltage drop
107	IF_DIODE1			10.0		Output rectifier rated average forward current
108						
109	<b>Output 2</b>					
110	VOUT2					Output voltage
111	IOUT2					Output current
112	POUT2					Output power
113	IRMS_SEC2					Secondary winding RMS current
114	IRIPPLE_COUT2					Output capacitor ripple current
115	NS2					Secondary winding number of turns
116	VDSOFF_DIODE2					Output rectifier off-time voltage stress (not incl. the parasitic ring)
117	PN_DIODE2					Suggested output rectifier schottky diode
118	VRRM_DIODE2					Output rectifier rated reverse repetitive voltage
119	VF_DIODE2					Output rectifier rated on-time voltage drop
120	IF_DIODE2					Output rectifier rated average forward current
121						
122	<b>Output 3</b>					
123	VOUT3					Output voltage
124	IOUT3					Output current
125	POUT3					Output power
126	IRMS_SEC3					Secondary winding RMS current
127	IRIPPLE_COUT3					Output capacitor ripple current
128	NS3					Secondary winding number of turns
129	VDSOFF_DIODE3					Output rectifier off-time voltage stress (not incl. the parasitic ring)
130	PN_DIODE3					Suggested output rectifier schottky diode
131	VRRM_DIODE3					Output rectifier rated reverse repetitive voltage
132	VF_DIODE3					Output rectifier rated on-time voltage drop
133	IF_DIODE3					Output rectifier rated average forward current
134						
135	POUT_TOTAL			120		Total output power
136	NEGATIVE OUTPUT	N/A		N/A		Select the negative output voltage index (Eg. Select 3 if you want the 3rd output to be negative)
137						